

Universal LED Bluetooth Dimmer

Bluetooth controllable dimming for SloanLED 12/24 VDC power supplies

- Bluetooth controllable 4-channel PWM dimmer
- Compatible with 12 VDC and 24 VDC SloanLED power supplies
- Over-voltage, over-current, and short circuit protection
- Configured and controlled via Casambi app, available for both iOS and Android devices



Specifications

Part number	601115
Dimensions L x W x H	2.2 in x 1.2 in x 0.7 in (72.6 mm x 30.0 mm x 18.0 mm)
Input	12-24 VDC, Class 2
Max. input current	4.0 A
No-load standby power	< 0.3 W
Max. output power	96 W @ 24 VDC 48 W @ 12 VDC
Max. output current	4.0 A (may be freely divided between channels)
Minimum load requirement	0 W
Dimming method	Pulse width modulation (PWM)
Operating frequencies	2.4 - 2.483 Ghz
Max. output power	+4 dBm
Operating temperature	-25° C to +45° C
Connectors	14 - 22 AWG
Protection class	IP20



Compatible devices:

Android 4.4 or later devices produced after 2013 with full BT 4.0 support
iPhone 4S or later
iPad 3 or later
iPod Touch 5th gen or later

SloanLED Headquarters
805.676.3200 • info@SloanLED.com

SloanLED Europe b.v.
+31 88 12 44 900 • Europe@SloanLED.com



SloanLED.com

© 2019 SloanLED Rev A 2019-04-10

Specifications subject to change without notice.

 **SloanLED**[®]
Leaders in LED Technology